



LUMASCAPE

MODELS LS275LED-3X2 3W Version

LS275LED-8X2 8W Version

IP68 rated FOR UNDERWATER USE



A IMPORTANT INSTRUCTIONS

For Installation LS275LED Underwater LED

Warning: The Luminaire should only be used complete with its protective shield (cover)

LUMASCAPE USA INC
1300 Industrial Rd, Unit #19
San Carlos, CA 94070, USA
T 1-(650)-595-LUMA(5862)
F 1-(650)-595-5820
E info@lumascope.com
W www.lumascope.com Free Call 1-866-695-LUMA(5862)

1

300MM (12IN) POWER OUTLET

Use an isolating type transformer and overcurrent protection for the secondary circuit as per The National Electrical Code (NEC).
Mount suitable transformer, (12v AC Magnetic transformer only) in appropriate location

2

75°
Screws to suit Ø6mm hole required
Ø52mm PCD

Mounting Base Dimension Details

Position fixtures and mark mounting hole locations. Drill holes to suit fasteners suitable for substrate, (Not supplied).

3

Loosen wing nut on pivot and remove base from fixture.
Attach fixture base to surface using appropriate fasteners.

4

Re-install fixture onto base

5

Aim fixture to required angle and tighten wing nut to fix.

IMPORTANT NOTE:
8W configuration must be submersed in order to operate.
Inbuilt Thermal Protection will turn fixture off if operated out of the water.

www.lumascope.com

LUMASCAPE
HEAD OFFICE
T 07 3286 2299 F 07 3286 6599

LUMASCAPE
SYDNEY - NSW
T 02 9519 6860 F 02 9519 8834

LUMASCAPE
MELBOURNE - VIC
T 03 9686 1900 F 03 9686 1700

H.I. LIGHTING
LUMASCAPE AGENT - WA
T 08 9321 5422 F 08 9321 5881

LIGHTING PARTNERS AUSTRALIA
LUMASCAPE AGENT - SA
T 08 8232 0074 F 08 8232 0076

NO LIGHTING
LUMASCAPE AGENT - NTH OLD
T 07 4031 4490 F 07 4031 5933

ECC LIGHTING
LUMASCAPE AGENT - NZ
T 09 379 9680 F 09 308 9328

LUMASCAPE USA INC
Free Call 1-866-695-LUMA(5862)
T 1-(650)-595-LUMA(5862) 1-(650)-595-5820